

DINGO Breakout Computer Board

Item specifications

Go-IoT Item Id:	DINGO-CB-BREAKOUT
USB	3 x USB 2.0 Type A Connectors 2 x USB Ports to Base Board
Serial Interface	2 x TTL Serial Debug Connectors 2 x TTL Ports to Base Board
I2C Ports	2 x Connectors
SPI Ports	1 x Connectors
Opto Input Status LEDs	8
Relay Switches	2
Reset Switch	1
Expansion Connectors	1 x 40way header to Base Board 1 x 20way header to Base Board 1 x 30way header to Display Board 21 x GPIO
DC Input	+12V @ 0.4A (internal power supply unit available as plug-in)
Temperature	-20 degree C to +85 degree C
Size (L x W x H)	101 x 60 x 15 mm
Country/Region of Manufacture:	EU

